


CEILING CENTERED BETWEEN BOARDS. MAIN MENUBOARD ROUGH-IN ELEVATION
NOT TO SCALE



REDHEAD ROASTER (RHR) POWER MONITOR SCHEMATIC

## **ELECTRICAL LEGEND** J JUNCTION BOX 20 AMP 120V-1PH HUBBELL #USB20X2BK RECEPTACLE \* = A-H AS COOKLINE JUNCTION BOXES REFER TO DETAIL #3 ON SHEET E4.2 20 AMP QUADRUPLEX 120V-1PH HUBBELL # USB20X2W (QTY 2) RT REMOTE TEST STATION (54") 20 AMP 120V-1PH SIMPLEX RECEPTACLE 0 20 AMP 120V-1PH HUBBELL #IG5362 +16" AFF OR AS NOTED ISOLATED GROUND RECEPTACLE PARTIAL CIRCUIT 20 AMP 120V-1PH DUPLEX RECEPTACLE 10 AMP QUAD HUBBELL #IG5362 (QTY 2) +16" AFF OR AS NOTED ISOLATED GROUND RECEPTACLE HOME RUN TO PANEL. 20 AMP 120V-1PH GROUND FAULT SPECIAL RECEPTACLE, SEE KITCHEN CIRCUIT NUMBERS, PHASE, INTERRUPTING RECEPTACLE EQUIPMENT SCHEDULE NEUTRAL & GROUND CONDUCTORS INDICATED DISCONNECT SWITCH BY ELECTRICAL ALONG WITH ISOLATED

CONTRACTOR

TELEPHONE CONNECTION

▼ TELEPHONE/DATA CONNECTION

DISCONNECT SWITCH SUPPLIED WITH

EQUIPMENT & CONNECTIONS														
		LOAD			VOLTAGE			CONNECTIONS		FEEDER				
CIRCUIT NUMBER	DESCRIPTION	HORSEPOWER	KILOWATTS	120V-IPH	208V-1PH	208V-3PH	120/208V-1PH	TYPE	PLUG CORD *	CONDUCTORS *	WIRE SIZE	GROUND SIZE	CONDUIT SIZE	NOTES
(E)	DRIVE THRU FREESTYLE		.7	0				EXIST. RECEPTACLE	ES	2	12	12	3/4"	EXISTING
(E)	POS MONITOR/TERMINAL		.3	0				RECEPTACLE	(E)					
(E)	POS MONITOR/TERMINAL		.3	0				RECEPTACLE	(E)					
(E)	BEVERAGE DISPENSER		.4	0				RECEPTACLE	ES	2	12	12	3/4"	EXISTING
			-	0				-	-	-	-	-	-	
	MENUBOARD		1.5	0				DIRECT	EC	2	12	12	3/4"	
	REDHEAD ROASTER		.5	0				DIRECT	EC	2	12	12	3/4"	
(E)	D.T. ICE MAKER		2.5		0			WP DISC SWITCH @ UNIT	ES	3	10	10	3/4"	VERIFY FOR REUSE
(E)	BEVERAGE DISPENSER		1.4	0				RECEPTACLE	ES	2	12	12	3/4"	
(E)	BEVERAGE ICE MAKER		2.5		0			WP DISC SWITCH @ UNIT	ES	3	10	10		
(E)	DOUBLE SIDED GRILL		15.9			0		RECEPTACLE NEMA 15-60	EC	3	6	10	1-1-1"	

| 12.8 | O | RECEPTACLE NEMA 15-50 | EC | 3 | 6 | 10 |  $1-\frac{1}{4}$ " |

ES /EQUIPMENT SUPPLIER
\* EC /ELECTRICAL CONTRACTOR


(E) DOUBLE SIDED GRILL

RECEPTACLE

R P 20 AMP 120V-1PH RECESSED RECEPTACLE

120V-1PH QUADRUPLEX RECEPTACLE

\*\* CONDUCTOR QUANTITY DOES NOT



## **GENERAL NOTES**

GROUND CONDUCTOR IF

THERMOSTAT, TEMPERATURE

SENSOR AND HUMIDISTAT

APPLICABLE.

BY MECHANICAL

- A. REFER TO "WIRING AND SITE PREPARATION GUIDE" AS PREPARED BY 'WENDY'S INTERNATIONAL' "INFORMATION SYSTEMS DEPARTMENT" FOR INSTALLATION OF POINT OF SALE CASH REGISTER SYSTEM.
- B. ELECTRICAL CONTRACTOR TO COORDINATE WORK WITH MECHANICAL, REFRIGERATION AND EQUIPMENT CONTRACTORS, INCLUDING COOLER/FREEZER WORK. (IF APPLICABLE)
- C. ELECTRICAL CONTRACTOR TO VERIFY ALL ROUGH-IN DIMENSIONS AND POWER REQUIREMENTS WITH KITCHEN EQUIPMENT DISTRIBUTOR PRIOR TO ROUGH-IN.
- D. ELECTRICAL CONTRACTOR TO HOOK UP FIELD CONNECTIONS WITHIN FRONT COUNTER, AND ICE MACHINE REMOTE UNIT (ON ROOF) AT TIME OF INSTALLATION.
- E. HEIGHTS INDICATED FOR RECEPTACLES AND JUNCTION BOXES ARE MEASURED FROM FINISH FLOOR TO THE
- CENTER OF THE BOX UNLESS OTHERWISE NOTED. F. ELECTRICAL CONTRACTOR IS RESPONSIBLE FOR INSTALLING ALL TELEPHONE LINES AND TERMINATIONS.
- VERIFY QUANTITY AND LOCATIONS WITH OWNER PRIOR TO BIDDING.
- G. ALL CIRCUITS MAY BE CORRECTED TO THE LEAST AMOUNT OF CONDUIT RUN UNLESS OTHERWISE NOTED. H. ALL COVER PLATES TO BE SATIN FINISH STAINLESS STEEL THROUGHOUT UNLESS OTHERWISE NOTED.
- ALL NEW 120V RECEPTACLES IN KITCHEN TO HAVE GROUND-FAULT CIRCUIT INTERRUPTER PROTECTION. OTHER GFI'S SHOWN SEPARATELY.
- J. FOR THE IBM POINT OF SALE REGISTER SYSTEM ONLY: ALTERNATE P.O.S. SUPPLIERS MUST CONFORM TO THE REGISTER LAYOUT OR PROVIDE THE OWNER AND/OR GENERAL CONTRACTOR WITH WIRING DIAGRAMS AND INSTALLATION DETAILS BEFORE THE ELECTRICAL CONTRACTOR STARTS ANY WORK.
- K. ALL CONDUITS SHOULD BE STEEL FLEX OR PLASTIC STUBBED OUT ABOVE THE CEILING LINE AND TERMINATED INTO A J-BOX AS NOTED AND CAPABLE OF ACCEPTING A FACEPLATE COVER.
- L. ALL J-BOXES SHOULD BE INSTALLED IN SUCH A WAY THAT THEY ARE NOT BLOCKED BY OTHER EQUIPMENT OR STRUCTURAL COMPONENTS.
- M. ALL IG OUTLETS (HUBBELL IG5362 ORANGE OR EQUAL) MUST BE CLEARLY LABELED.
- N. ALL CABLE ACCESS OPENINGS THRU S/S MUST HAVE RUBBER OR PLASTIC GROMMETS INSTALLED.
- O. THE ELECTRIC SERVICE FOR THE GFI OUTLET/SCOREBOARD MUST BE ON A SEPARATE BREAKER (NOT CONNECTED TO THE MENU BOARD OR OUTSIDE LIGHT FEED).
- P. HEIGHTS INDICATED FOR RECEPTACLES AND J-BOXES ARE MEASURED FROM FINISH FLOOR TO THE CENTER OF BOX. U.N.O.
- Q. EXISTING ENERGY MANAGEMENT SYSTEM TO REMAIN AND BE FULLY OPERATIONAL AT COMPLETION OF
- REMODEL.
- R. ALL CUSTOMER ACCESSIBLE RECEPTACLES MUST BE TAMPER RESISTANT.

## X CODED NOTES:

- 1. CIRCUIT TO EXISTING 20A, 120V, SPARE CIRCUIT BREAKER AS INDICATED ON PLANS IN EXISTING PANELBOARD (FIELD VERIFY). VERIFY THAT THE ADDITIONAL LOAD DOES NOT OVERLOAD EXISTING PANELBOARD OR ANY UPSTREAM ELECTRICAL DEVICE.
- 2. ALL EXISTING ELECTRICAL DEVICES, CONDUIT, WIRING, AND EQUIPMENT IN THIS AREA AND ON ROOF TO REMAIN, UNLESS NOTED OTHERWISE, MAINTAIN AND PROTET EXISTING BRANCH CIRCUITS.
- 3. PROVIDE POWER AND DATA FOR STATIC MENUBOARDS. PROVIDE CIRCUITING TO MENU BOARDS IN SERVING AREA VIA LIGHTING CONTACTOR. DESIGN INTENT IS FOR MENU BOARDS TO BE CONTROLLED ON AND OFF WITH GENERAL LIGHTING IN THIS AREA.
- 4. PROVIDE CEILING MOUNTED DUPLEX RECEPTACLE AND DATA FOR DIGITAL RHR MONITOR. SEE RHR POWER MONITOR SCHEMATIC DETAIL ON THIS SHEET.
- PROVIDE POWER AND DATA FOR QUEUING BOARDS. PROVIDE CIRCUITING TO QUEUING BOARDS IN SERVING AREA VIA LIGHTING CONTACTOR. DESIGN INTENT IS FOR QUEUING BOARDS TO BE CONTROLLED ON AND OFF WITH GENERAL LIGHTING IN THIS AREA.

SITE NUMBER: **BUILDING TYPE:** 3076 ASSET TYPE: FREE STANDING **CLASSIFICATION:** REFRESH OWNER: STARBOARRD BASE VERSION: 2021 SPRING

UPGRADE CLASSIFICATION:

PROJECT YEAR: 2022 DESIGN TYPE: (2.0) UM BRIGHT DRAWING RELEASE: 2021 SPRING





STARBOARD GROUP 12540 W. ATLANTIC BLVD. CORAL SPRINGS, FL 33071 OFFICE: (954)255-2266

REV. DATE DESCRIPTION

ISSUE DATE: 12/09/2021

PROJECT NUMBER: 21-121 DRAWN BY: MS/BS CHECKED BY: AR/CF



POWER PLAN